



MEDIUM FIDELITY OUTPUT TRANSFORMERS

(1) OPM SERIES—40-12000 C.P.S. \pm 2 db. (2)

FERGUSON offer a complete range of reasonably priced MEDIUM FIDELITY OUTPUT TRANSFORMERS ideally suited for radiograms, record players, public address amplifiers, etc., where the use of a higher priced true high-fidelity type is not justified.

TYPE No.	NOM. POWER (WATTS)	PRIMARY IMPEDANCE (OHMS)	SECONDARY IMPEDANCE (OHMS)	MTG. STYLE
OPM1	5	S.E. 7000, 5000	15, 12.5, 8, 3.7, 3.1, 2	1
OPM19	5	S.E. 7000, 5000	500, 250, 166, 125	1
OPM20	5	S.E. 10000, 8000	15, 12.5, 8, 3.7, 3.1, 2	1
OPM2	7	P.P. 10000	15, 12.5, 8, 3.7, 3.1, 2	1
OPM3	10	S.E. 4000, 2500	15, 12.5, 8, 3.7, 3.1, 2	2
OPM4	10	S.E. 4000, 2500	500, 250, 166, 125	2
OPM5	15	P.P. 5000, 3000	15, 12.5, 8, 3.7, 3.1, 2	2
OPM6	15	P.P. 5000, 3000	500, 250, 166, 125, 100	2
OPM7	15	P.P. 10000, 8000, 7000	15, 12.5, 8, 3.7, 3.1, 2	2
OPM8	15	P.P. 10000, 8000, 7000	500, 250, 166, 125, 100	2
OPM10	25	P.P. 8000, 6600	15, 12.5, 8, 3.7, 3.1, 2	2
OPM9	25	P.P. 8000, 6600	500, 250, 166, 125, 100	2
OPM14	35	P.P. 8000, 6600	15, 12.5, 8, 3.7, 3.1, 2	2
OPM11	35	P.P. 8000, 6600	500, 250, 166, 125, 100, 71	2
OPM13	55	P.P. 3500	15, 12.5, 8, 3.7, 3.1, 2	2
OPM12	55	P.P. 3500	500, 250, 125, 83, 62, 50	2
UNIVERSAL TEST SPEAKER				
OPM15	10	P.P. or S.E. 10000, 7000, 5000, 2500	3.1	2
LINE TO VOICE COIL				
OPM16	10	500	15, 12.5, 8, 3.7, 3.1, 2	1
OPM17	15	500	15, 12.5, 8, 3.7, 3.1, 2	2
OPM18	25	500	15, 12.5, 8, 3.7, 3.1, 2	2

Individual data sheets on all types available on request.

Available from all leading suppliers throughout Australia

MANUFACTURED BY

FERGUSON TRANSFORMERS PTY. LTD.

411 VICTORIA AVENUE, CHATSWOOD, N.S.W. JA8491

MELBOURNE—McKINNON NICHOLLS PTY. LTD.,
468 Collins St., MB1501.

BRISBANE—KEITH PERCY & CO., PTY. LTD.,
179 Elizabeth St., 2-1757

ADELAIDE—TYQUIN LTD., 13 Deacon Ave., Richmond,
57-8153, 57-8154, 57-7887

PERTH—ATHOL M. HILL, Durham House,
842 Hay St., 21-6987



POWER TRANSFORMERS

FERGUSON offer a wide range of power transformers for radio, TV, amplifiers, and electronic equipment generally. These transformers provide quality, performance, and reliability at reasonable prices.

For further details, contact your usual supplier.

TYPE No.	PRIMARY VOLTS	H.T. Volts	H.T. D.C.M.A.	L.T. SECONDARIES
PF619	240	150-0-150	30	6.3V-1.8A
PF185	240	150-0-150	30	6.3V-2A
PF299	240	285-0-285	40	6.3V-2A, 6.3V-tapped 5V-2A
PF300	240	325-0-325	40	6.3V-2A, 5V-2A
PF201	240	225-0-225	50	6.3V-2A
PF1459	230, 240, 250	250-0-250	60	6.3V-2AC.T., 6.3V-tapped 5V-2A
PF151	230, 240	285-0-285	60	6.3V-2AC.T., 6.3V-tapped 5V-2A
PF1388	230, 240	300-0-300	60	6.3V-2AC.T., 6.3V-tapped 5V-2A
PF166	230, 240	325-0-325	60	6.3V-2AC.T., 6.3V-tapped 5V-2A
PF165	230, 240	385-0-385	60	6.3V-2AC.T., 5V-2A
PF1460	230, 240, 250	250-0-250	80	6.3V-2AC.T., 6.3V-tapped 5V-2A
PF1428	230, 240, 250	250-0-250	80	6.3V-2AC.T., 6.3V-0.6A
PF170	230, 240	285-0-285	80	6.3V-2AC.T., 6.3V-2A, 6.3V-tapped 5V-2A
PF1073	230, 240	300-0-300	80	6.3V-2AC.T., 6.3V-1A
PF169	230, 240	325-0-325	80	6.3V-2AC.T., 6.3V-2A, 6.3V-tapped 5V-2A
PF168	230, 240	385-0-385	80	6.3V-2AC.T., 6.3V-2A, 5V-2A
PF1509	200, 230, 240	140 *	100	6.3V-2AC.T., 6.3V-2A
PF130	230, 240	285-0-285	100	6.3V-2AC.T., 6.3V-2A, 6.3V-tapped 5V-2A
PF164	230, 240	325-0-325	100	6.3V-2AC.T., 6.3V-2A, 6.3V-tapped 5V-2A
PF160	230, 240	385-0-385	100	6.3V-2.5AC.T., 6.3V-2A, 5V-2A
PF1072	230, 240	300-0-300	120	6.3V-4AC.T., 6.3V-tapped 5V-2A
PF152	230, 240	285-0-285	125	6.3V-3AC.T., 6.3V-2A, 6.3V-tapped 5V-2A
PF163	230, 240	325-0-325	125	6.3V-2.5AC.T., 6.3V-2A, 6.3V-tapped 5V-2A
PF181	230, 240	385-0-385	125	6.3V-3AC.T., 6.3V-3A, 5V-2A
PF1508	230, 240, 250	250-0-250	150	6.3V-4AC.T., 6.3V-tapped 5V-2A
PF174	230, 240	285-0-285	150	6.3V-3AC.T., 6.3V-3A, 6.3V-tapped 5V-3A
PF142	230, 240	325-0-325	150	6.3V-2AC.T., 6.3V-2A, 6.3V-tapped 5V-3A
PF175	230, 240	385-0-385	150	6.3V-2AC.T., 6.3V-2A, 5V-3A
PF173	230, 240	425-0-425	175	6.3V-3AC.T., 6.3V-2A, 5V-3A
PF1335	230, 240	305-0-305	180	6.3V-4AC.T., 6.3V-4A, 5V-3A
PF1067	230, 240	400-0-400	180	6.3V-2.5AC.T., 6.3V-4AC.T., 5V-3A
PF1412	230, 240	300-0-300	200	6.3V-3.5AC.T., 6.3V-3A, 5V-3A
PF172	200, 230, 240	500-0-500	200	6.3V-4AC.T., 6.3V-3A, 5V-3A
PF814	200, 230, 240	1000-0-100C or 750-0-750 or 500-0-500	200 250 300	5.5V-0.3A
PF179	200, 230, 240	475-0-475	225	6.3V-4AC.T., 6.3V-2A, 5V-3A
PF171	200, 230, 240	385-0-385	250	6.3V-4AC.T., 6.3V-3A, 5V-3A
PF107	230, 240	585-0-585	250	6.3V-3A, 6.3V-3A, 5V-3A
PF1193	200, 220, 240	295-0-295	275	6.3V-9A, 6.3V-tapped 5V-3A
PF1193V	200, 220, 240	295-0-295	275	6.3V-9A, 6.3V-tapped 5V-3A
PF1448	230, 240, 250	115*	300	12.6V C.T.-5A

* Voltage Doubler Types

Manufactured by

FERGUSON TRANSFORMERS PTY. LTD.

FERGUSON LANE, CHATSWOOD, N.S.W. JA8491